



Tech Info Library

Numeric Keypad IIe Internal Cable: Pinouts (10/94)

Revised: 10/13/94
Security: Everyone

Numeric Keypad IIe Internal Cable: Pinouts (10/94)

Article Created: 11 September 1986
Article Reviewed/Updated: 13 October 1994

TOPIC -----

What are the pinouts for the IIe numeric keypad?

DISCUSSION -----

Here is the wiring for the internal cable that goes from the Apple IIe motherboard connector to the DB-15 on the back of the Numeric Keypad IIe.

J16 PIN	DB-15	14 PIN CONN.	SIGNAL
1	---	12	Y0
2	---	5	Y1
3	---	8	Y3
4	---	2	Y4
5	---	7	Y2
6	---	4	Y5
7	---	N/C	N/C
8	---	1	X7
9	---	6	X4
10	---	10	X6
11	---	9	X5

J16 PIN - Internal (motherboard) connector
DB-15 - External connector (mounts in back of IIe with the Internal Keypad Cable (Part #590-0129))
14-PIN - Female connector that plugs into keypad
SIGNAL - What it does

Article Change History:
13 Oct 1994 - Reviewed for technical accuracy, revised formatting.

Support Information Services

Copyright 1986-94 Apple Computer, Inc.

Tech Info Library Article Number:1040